

EHD Components 2005 (Pty) Ltd

E-mail:

JHB: ehd@ehd.co.za
 CPT: ehdcapetown@ehd.co.za
 DBN: ehd.dbn@ehd.co.za
 BLOEM: ehdbloem@ehd.co.za

Contact Number:

JHB: +27 (0)11 870 5000
 CPT: +27 (0)21 510 0567
 DBN: +27 (0)31 700 1160
 BLOEM: +27 (0)51 430 5404

Open Diesel Generator

Open Diesel Generator

Model	MDG6000CL	MDG3600CL
Frequency	50	50
Max. AC output (kw)	5	3.3
Cont. AC output (kw)	4.5	3
Rated Current (A)	20.5	12.3
Voltage (V)	110; 115; 120; 220; 110/220; 115/230; 120/240	
D.C. output (V-A)	12/8.3	12.3/8.3
Power Factor	1	1
Engine Model	MD186FG	MD178FG
Displacement (cc) / (cu.in)	418/25.5	296/18.06
Engine Speed (rpm)	3000	3000
Lube Oil Capacity (L) / (US.Gal)	1.65/0.44	1.1/0.29
Fuel Tank Capacity (L) / (US.Gal)	12.5/3.3	12.5/3.3
Dimensions (LxWxH) (mm) / (inch)	740*475*590	680*455*545
	29.1*18.7*23.2	26.7*17.9*21.4
Net Weight (kg) / (lbs)	88/194.007	70/154.324

Disclaimer

Manufacturer's names, numbers, symbols, photos and descriptions are used for reference purposes only and it is not implied that the parts referred to are the products of those manufacturers

Source: www.ehd.co.za