

# EHD Components 2005 (Pty) Ltd

**E-mail:**

JHB: ehd@ehd.co.za  
 CPT: ehdcapetown@ehd.co.za  
 DBN: ehd.dbn@ehd.co.za  
 BLOEM: ehdbloem@ehd.co.za

**Contact Number:**

JHB: +27 (0)11 870 5000  
 CPT: +27 (0)21 510 0567  
 DBN: +27 (0)31 700 1160  
 BLOEM: +27 (0)51 430 5404

## Open Diesel Generator

# Open Diesel Generator

Model	MDG6000CL	MDG3600CL
Frequency	50	50
Max. AC output (kw)	5	3.3
Cont. AC output (kw)	4.5	3
Rated Current (A)	20.5	12.3
Voltage (V)	110; 115; 120; 220; 110/220; 115/230; 120/240	
D.C. output (V-A)	12/8.3	12.3/8.3
Power Factor	1	1
Engine Model	MD186FG	MD178FG
Displacement (cc) / (cu.in)	418/25.5	296/18.06
Engine Speed (rpm)	3000	3000
Lube Oil Capacity (L) / (US.Gal)	1.65/0.44	1.1/0.29
Fuel Tank Capacity (L) / (US.Gal)	12.5/3.3	12.5/3.3
Dimensions (LxWxH) (mm) / (inch)	740*475*590	680*455*545
	29.1*18.7*23.2	26.7*17.9*21.4
Net Weight (kg) / (lbs)	88/194.007	70/154.324

## Disclaimer

Manufacturer's names, numbers, symbols, photos and descriptions are used for reference purposes only and it is not implied that the parts referred to are the products of those manufacturers

**Source: [www.ehd.co.za](http://www.ehd.co.za)**