

# EHD Components 2005 (Pty) Ltd

**E-mail:**

JHB: ehd@ehd.co.za  
 CPT: ehdcapetown@ehd.co.za  
 DBN: ehd.dbn@ehd.co.za  
 BLOEM: ehdbloem@ehd.co.za

**Contact Number:**

JHB: +27 (0)11 870 5000  
 CPT: +27 (0)21 510 0567  
 DBN: +27 (0)31 700 1160  
 BLOEM: +27 (0)51 430 5404

## Open Diesel Generator

# Open Diesel Generator

| Model                             | MDG6000CL                                     | MDG3600CL      |
|-----------------------------------|---|----------------|
| Frequency                         | 50  | 50             |
| Max. AC output (kw)               | 5   | 3.3            |
| Cont. AC output (kw)              | 4.5   | 3              |
| Rated Current (A)                 | 20.5  | 12.3           |
| Voltage (V)                       | 110; 115; 120; 220; 110/220; 115/230; 120/240 |                |
| D.C. output (V-A)                 | 12/8.3  | 12.3/8.3       |
| Power Factor                      | 1   | 1              |
| Engine Model                      | MD186FG                                       | MD178FG        |
| Displacement (cc) / (cu.in)       | 418/25.5                                      | 296/18.06      |
| Engine Speed (rpm)                | 3000  | 3000           |
| Lube Oil Capacity (L) / (US.Gal)  | 1.65/0.44                                     | 1.1/0.29       |
| Fuel Tank Capacity (L) / (US.Gal) | 12.5/3.3                                      | 12.5/3.3       |
| Dimensions (LxWxH) (mm) / (inch)  | 740*475*590                                   | 680*455*545    |
|                                   | 29.1*18.7*23.2                                | 26.7*17.9*21.4 |
| Net Weight (kg) / (lbs)           | 88/194.007                                    | 70/154.324     |

## Disclaimer

Manufacturer's names, numbers, symbols, photos and descriptions are used for reference purposes only and it is not implied that the parts referred to are the products of those manufacturers

**Source: [www.ehd.co.za](http://www.ehd.co.za)**