

# EHD Components 2005 (Pty) Ltd

**E-mail:**

JHB: ehd@ehd.co.za  
 CPT: ehdcapetown@ehd.co.za  
 DBN: ehd.dbn@ehd.co.za  
 BLOEM: ehdbloem@ehd.co.za

**Contact Number:**

JHB: +27 (0)11 870 5000  
 CPT: +27 (0)21 510 0567  
 DBN: +27 (0)31 700 1160  
 BLOEM: +27 (0)51 430 5404

MG11000CLE

## MG11000CLE

	Model	MG11000CLE
Generator	AC Frequency (HZ)	50
	AC Output Voltage (V)	110;120;220;240;110/220;120/240
	Rated AC Output (kw)	8.5
	DC Output	12/8.3
	Rated Current	38.6A
Engine	Engine Model	M620
	Starting System	Electric
	Fuel Tank Capacity	25/6.6
	(L)/(US.Gal)	
	Oil Capacity (L)/(US.Gal)	1.5
Rated Speed(rpm)	3000	
Unit	Dimensions (LxWxH)	985x700x1085
	(mm) / (inch)	35.2x24.4x29.5
	Net Weight (kg)/(lbs)	190/418.878

**Characteristics:**

1. Powered by MELLGA 4-Stroke OHV petrol Engine
2. Circuit breaker protects overload operation.
3. Large fuel tank ensures 8 hours of continuous running
4. AVR alternator provides stable voltage and current.
5. Emergency low oil alert warn the low lube oil level.

## Disclaimer

Manufacturer's names, numbers, symbols, photos and descriptions are used for reference purposes only and it is not implied that the parts referred to are the products of those manufacturers

Source: [www.ehd.co.za](http://www.ehd.co.za)